

10W Rechargeable LED PRO Floodlight 1300Lm with Powerbank Function

Product codes:

Reference: PR10W



Product features:

Power (W): 10
Power source (V): 220-240V
Color temperature CCT: 6500K
LED: SMD2835
Brightness (Lm): 1300
CRI: +70
Colour: Grey
IP: IP54
IK: IK10
Luminous angle: 120°
Measures (mm): 195x168x260mm
Operating temperature: -20°C ~ +40°C
Lifespan: 25.000h
Certification: CE - RoHS
Warranty: 3 años

Product attributes:

Color temperature CCT (°K): Cool white 6000K

Product description:

Rechargeable LED Floodlight 10W 1300Lm The **rechargeable LED floodlight** 10W is a portable and versatile lighting solution, perfect for a variety of indoor and outdoor applications. With a luminous flux of 1300 lumens, this LED floodlight provides bright and clear cool white 6500K light.

Constructed with a durable grey and orange nylon housing and a PC diffuser, this floodlight is equipped with a high-brightness SMD2835 LED chip. Its design, adjustable up to 90°, allows the light direction to be tailored to specific needs, making it ideal for DIY projects, camping, emergencies, and more.

Features of the Rechargeable LED Floodlight

- **Power:** 10W
- **Luminous Flux:** 1300 lumens
- **Material:** Grey and orange nylon housing, PC diffuser
- **LED Chip:** High-brightness SMD2835
- **Adjustable:** Up to 90°

- **Working Modes:** 100% and 50%
- **Battery:** High-performance LiFePO4
- **Runtime:** Up to 3h at 100%, 6h at 50%
- **Charging:** Includes USB charging cable
- **Powerbank Function:** Charges other devices at 5V
- **Light Color:** Cool white 6500K
- **IP Rating:** IP54, resistant to splashes, dust, and humidity
- **Dimensions:** 195x168x260mm
- **Luminous Angle:** 120°

Applications of the Rechargeable LED Floodlight

The **rechargeable LED floodlight** is ideal for a variety of uses, including:

- DIY projects and home repairs
- Camping and outdoor activities
- Emergency situations and power outages
- Temporary lighting for events and parties
- Use in garages, basements, and other work areas

Product gallery:

