LED Push-Button Dimmer - TRIAC

Product codes:

Reference: IL-4705



Product features:

Power (W): 300
Power source (V): 220-240V
Dimmable: Sí, TRIAC
IP: IP20
Measures (mm): 47x47x14mm
Material: Aluminum + PC
Operating temperature: -20ºC ~ +55ºC
Certification: CE - RoHS
Warranty: 3 años

Product attributes:

Product description:

Recessed TRIAC dimmer, thermal protection Push-button TRIAC Dimmer for LED 5-95% max 300W IP20

The for AC 220-240V ON-OFF systems adjusts the intensity from of all TRIAC-compatible dimmable LED luminaires. Max load , flush-box format (47x47x14 mm), overload and thermal protection, IP20, 3-year warranty.

? TRIAC? 5-95%? Max 300W? IP20

TRIAC
Technology5-95%

Dimming300W
Max load220-240V
Voltage

The **push-button TRIAC LED dimmer** is designed for AC 220-240V ON-OFF systems and adjusts the emitted light intensity from **5 to 95%** on all dimmable luminaires that accept TRIAC LED dimming. It supports a maximum load of 300W in LED lighting.

Designed to the dimensions of a **flush mounting box (47x47x14 mm)**, it integrates discreetly into the existing installation. It has **overload protection and thermal protection** for safe, durable operation. IP20-rated, it is used indoors. 3-year warranty.

Why choose this product? **? 5-95% dimming**

Adjust the intensity of TRIAC dimmable LED luminaires. **? Max load 300W**

Compatible with many LED installations. **? Built-in protections**

Overload and thermal, flush-box format. Technical specifications Product typePush-button TRIAC dimmer for LEDTechnologyTRIACDimming range5 to 95%Maximum load300W (LED)VoltageAC 220-240VDimensions47x47x14 mm (mounting box)ProtectionsOverload and thermalProtectionIP20Warranty3 years Advantages

- **5-95% dimming:** on TRIAC LED luminaires.
- **Max load 300W:** wide compatibility.
- **Push-button:** 220-240V ON-OFF system.
- **Flush-box format:** discreet integration.
- **Protections:** overload and thermal.
- **IP20, 3-year warranty:** indoor use.

Recommended applications ?**Homes** — LED lighting dimming.?**Hotels and restaurants** — adjustable atmospheres.?**Offices and shops** — intensity control.?**Living rooms and bedrooms** — variable lighting. Installation guide 1**Switch off the power**
Cut the supply before installation.2**Place in the box**
Insert the dimmer into the mounting box.3**Wire it**
Wire the dimmer between the supply and the TRIAC LED luminaire.4**Adjust**

Restore power and set the intensity (5-95%) with the push-button. Frequently asked questions **What maximum load does it support?**

Up to 300W in LED lighting. **What is the dimming range?**

From 5 to 95%, on TRIAC-compatible LED luminaires. **Where is it installed?**
In a standard mounting box (47x47x14 mm). ?

TRIAC
5-95%?

300W
220-240V?

Protections
IP20?

Warranty
3 years


Product gallery:



Hide in the wire box to save installation space,Better visual appearance
Main features: the wi-fi switch module designed to trans-form your traditions switch into wi-fi smart switch
Note: It's Only Suit For Push Button Switch
Mini design. Hidden in the wire box!






47mm
H14mm
47mm
LED


N
F
1
2
3
4


1
2
3
4
F
N